



EKSELANS BY ITS

REPARTIDORES CON CONECTOR F

RI 2 / RF 12 / RF 13 / RF 14 / RF 16 / RF 18

Factor de apantallamiento clase A
Paso de corriente en todas las salidas
5-2400 MHz

REFERENCIA		RI 2	RF 12	RF 13	RF 14	RF 16	RF 18
Código		141006	141001	141002	141003	141004	141005
Banda de paso	MHz	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400
Salidas	Nº	2	2	3	4	6	8
Pérdidas de paso	dB 860 MHz	4	4	7	8,1	11	12
	dB 2400 MHz	5,5	5,5	9,5	10	14,5	15,5
Desacoplo entre salidas	dB	>20	>20	>20	>20	>20	>20
Perdidas de retorno	dB	>10	>10	>10	>10	>10	>10
Paso de corriente	mA	800	800	800	800	800	800



RI 2



PMM

Protección intemperie RI 2 (opcional)

REFERENCIA		PMM
Código		024001



RF 12



RF 13 / RF 14



RF 16 / RF 18